

Quick Start Guide

Getting to know your device

Put the SIM card

The SIM card is not included in the package. A Nano SIM card is available from the user's local operator.

- Unscrew the back cover and remove.
- Insert the SIM card and make sure it's activated with credits.
- Put the cover back and tighten the screws.

TIP Before installing the SIM card, check if the SIM card has PIN code or not. If yes, please use a cell-phone to remove the card's PIN code.

Charging your device

There are two ways to charge your device.

1/ charging base

- Place the device on the charging base.
- Connect the USB cable from charging base to the AC adaptor.

The charging base light will glow when charging and turn solid when fully charged.

2/ Wireless Charging

- A Qi charger provides a quick charging and easy to use.
- The wireless charging pad is not included in the package.

Switching on and off device

- To turn on the device:** press the CALL button for 1 second, all the LEDs will flash rapidly. The device can also be turned on automatically by charging via magnetic USB cable or put it into the docking station.
- To turn off the device:** press and hold the side button and SOS button together for 3 seconds until the LEDs turn off.

What do the lights mean?

Cellular signal indicator-Green

Green	Light shows a single flash rapidly every 3 seconds	Light shows a double flash rapidly every 3 seconds
Means	The device has a stable cellular signal	The device is registered to the cellular network

Positioning indicator-Blue

Blue	Light shows a single flash rapidly every 3 seconds	Light shows a double flash rapidly every 3 seconds	Light Off
Means	The device has no latest location fix	The device has latest location fix	The device is not fixing the latest location

Power indicator-Red

Red	Red ON (solid)	Red shows a double flash rapidly every 3 seconds
State	Device has been fully charged	BLE connected

Red	Red Blinking Quickly	Red Off or blinking slowly
State	Battery power is lower than 20%	The device is charging

Activating an SOS Alarm

When you need help, press the SOS button for 3-4 seconds till you hear a voice prompt of activating an SOS alarm. This starts the sequence of "help me!" text message send to your emergency contact numbers followed by the outgoing calls.

- If the device fails to connect to the first number, it will call the second number after delay of 10 seconds. In case the second number fails to be connected as well, the system will connect to the third number etc.

Getting a GPS fix

- To get an initial fix for the GPS features, use outdoors or near a window so the device can get a fix on the satellites. This could take few minutes according to your environment.

Making a Phone Call

- To make a call, press side call button for 3 seconds and you will hear a beep, and then it will dial the second number.
- To end the call, press the SOS button.

Silent mode button

- Double-click this button to **turn off voice warnings**, double-click the button again to **turn on voice warnings**.
- Put device on charging base more than 30 seconds, and they will be paired automatically via Bluetooth.

Specification:

- Dimension: 62mm*47mm*17mm
- Weight: 53g
- Battery: Rechargeable, 3.7V, 1000mAh
- Charging voltage: 5V DC
- Waterproof: IP67
- 4 locating technologies: GPS, BLE, WIFI, LBS

Cautions:

Please comply with the instructions to extend the unit life:

- Don't use & store the unit in dusty places.
- Don't put the unit in overheated or over cooled places.
- Clean the unit with a piece of dry cloth. Don't clean in chemicals, detergent.
- Don't disassemble or refit the unit.
- Using other batteries will cause unwanted situation.

Warning: Keep the IMEI and SIM in confidential, or your privacy may expose.

FCC Statement

1. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference.

(2) This device must accept any interference received, including interference that may cause undesired operation.

2. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna.

Increase the separation between the equipment and receiver.

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.

SAR Information Statement

Your wireless phone is a radio transmitter and receiver. It is designed and manufactured not to exceed the emission limits for exposure to radiofrequency (RF) energy set by the Federal Communications Commission of the U.S. Government. These limits are part of comprehensive guidelines and establish permitted levels of RF energy for the general population. The guidelines are based on standards that were developed by independent scientific organizations through periodic and thorough evaluation of scientific studies. The standards include a substantial safety margin designed to assure the safety of all persons, regardless of age and health. The exposure standard for wireless mobile phones employs a unit of measurement known as the Specific Absorption Rate, or SAR. The SAR limit set by the FCC is 1.6 W/kg. * Tests for SAR are conducted with the phone transmitting at its highest certified power level in all tested frequency bands. Although the SAR is determined at the highest certified power level, the actual SAR level of the phone while operating can be well below the maximum value. This is because the phone is designed to operate at multiple power levels so as to use only the power required to reach the network. In general, the closer you are to a wireless base station antenna, the lower the power output. Before a phone model is available for sale to the public, it must be tested and certified to the FCC that it does not exceed the limit established by the government adopted requirement for safe exposure. The tests are performed in positions and locations (e.g., at the ear and worn on the body) as required by the FCC for each model. The highest SAR value for this Personal Mobile Alarm System when tested for Front to Face is [0.635W/Kg](#) and when worn on the body, as

described in this user guide, is 1.235W/Kg (Body-worn measurements differ among phone models, depending upon available accessories and FCC requirements). While there may be differences between the SAR levels of various phones and at various positions, they all meet the government requirement for safe exposure. The FCC has granted an Equipment Authorization for this Personal Mobile Alarm System with all reported SAR levels evaluated as in compliance with the FCC RF exposure guidelines. SAR information on this Personal Mobile Alarm System is on file with the FCC and can be found under the Display Grant section of <http://www.fcc.gov/oet/fccid> after searching on

[FCC ID: 2AUMJEV-04-LTE](#) Additional information on Specific Absorption Rates (SAR) can be found on the Cellular Telecommunications Industry Association (CTIA) web-site at <http://www.wow-com.com>. * In the United States and Canada, the SAR limit for mobile phones used by the public is 1.6 watts/kg (W/kg) averaged over one gram of tissue. The standard incorporates a substantial margin of safety to give additional protection for the public and to account for any variations in measurements.

Body-worn Operation

This device was tested for typical body-worn operations. To comply with RF exposure requirements, a minimum separation distance

of 10mm must be maintained between the user's body and the handset, including the antenna. Third-party belt-clips, holsters, and similar accessories used by this device should not contain any metallic components. Body-worn accessories that do not meet these requirements may not comply with RF exposure requirements and should be avoided. Use only the supplied or an approved antenna.